

Approximation by power series with ± 1 coefficients

C. Sinan Güntürk

February 1, 2008

Abstract

In this paper we construct certain type of near-optimal approximations of a class of analytic functions in the unit disc by power series with two distinct coefficients. More precisely, we show that if all the coefficients of the power series $f(z)$ are real and lie in $[-\mu, \mu]$ where $\mu < 1$, then there exists a power series $Q(z)$ with coefficients in $\{-1, +1\}$ such that $|f(z) - Q(z)| \rightarrow 0$ at the rate $e^{-C/|1-z|}$ as $z \rightarrow 1$ non-tangentially inside the unit disc. A result by Borwein-Erdélyi-Kós shows that this type of decay rate is best possible. The special case $f \equiv 0$ yields a near-optimal solution to the “fair duel” problem of Konyagin.

1 Introduction

This paper is motivated by the “fair duel” problem which the author heard from S. Konyagin [1]. The problem is the following: There are two duellists X and Y who will shoot at each other (only one at a time) using a given ± 1 sequence $q = (q_n)_{n \geq 0}$ which specifies whose turn it is to shoot at time n . The shots are independent and identically distributed random variables with outcomes hit or miss. Each shot hits (and therefore kills) its target with small unknown probability ϵ , which is arbitrary but fixed throughout the duel. The “fair duel” problem is to find an ordering q , which is independent of ϵ , and is as fair as possible in the sense that the probability of survival for each duellist is as close to $1/2$ as possible. We measure the fairness of an ordering q by its *bias* function $B_q(\epsilon)$, defined to be

$$B_q(\epsilon) := \mathbb{P}\{X \text{ survives}\} - \mathbb{P}\{Y \text{ survives}\},$$

and ask that $B_q(\epsilon) \rightarrow 0$ as $\epsilon \rightarrow 0$ as fast as possible.¹

It is elementary to calculate the bias in terms of q . Given that the duel is not over before time n , which happens with probability $(1 - \epsilon)^n$, the probability that Y is shot at time n is equal to ϵ if it is the turn of X to shoot, and 0 otherwise. By symmetry of the problem, we find

$$\mathbb{P}\{Y \text{ dies at time } n\} - \mathbb{P}\{X \text{ dies at time } n\} = \epsilon q_n (1 - \epsilon)^n,$$

where we have assumed that $q_n = +1$ labels the turn of X and $q_n = -1$ labels the turn of Y . Summing over n , we obtain

$$B_q(\epsilon) = \epsilon \sum_{n=0}^{\infty} q_n (1 - \epsilon)^n.$$

¹The problem makes sense only when we ask q to be universal, i.e., independent of ϵ . Otherwise, for any $\epsilon \leq 1/2$, the bias can be made zero by mapping the fractional β -expansion of the number $1/(2\epsilon)$ in the basis $\beta = 1/(1 - \epsilon)$ to an ordering [1].

At first, it may appear as the best ordering should be to simply alternate between X and Y , i.e., to set $q_n = (-1)^n$, for which $B_q(\epsilon) = \epsilon/(2 - \epsilon) = \Theta(\epsilon)$. However, this naive option is quickly ruled out as for instance the 4-periodic sequence given by $q_0 = 1, q_1 = -1, q_2 = -1, q_3 = 1$ yields $B_q(\epsilon) = \epsilon^2/(1 + (1 - \epsilon)^2) = \Theta(\epsilon^2)$. Continuing in this fashion, it is tempting to think that the Thue-Morse sequence on the alphabet $\{-1, +1\}$ (see, e.g. [2]) might perhaps be the optimal sequence. For the Thue-Morse sequence, one has

$$B_{\text{TM}}(\epsilon) = \epsilon \prod_{n=0}^{\infty} (1 - (1 - \epsilon)^{2^n}),$$

where the infinite product $\prod (1 - z^{2^n}) = \sum q_n z^n$ can in fact be taken as the definition of this sequence. It is not difficult to show that there is a positive constant $c > 0$ such that $B_{\text{TM}}(\epsilon) = \Omega(e^{-c(\log \epsilon)^2})$. (See Section 3.2 for a short derivation.)

It turns out that one can do much better. One special outcome of this paper will be the construction of universal orderings q for which $B_q(\epsilon) = O(e^{-c/\epsilon})$ where $c > 0$ is an absolute constant. In fact, we shall prove the following more general result:

Theorem 1. *Let $0 \leq \mu < 1 \leq M < \infty$ be arbitrary and $\mathcal{R}_M := \{z \in \mathbb{C} : |1 - z| \leq M(1 - |z|)\}$. There exist constants $C_1 := C_1(\mu, M) > 0$ and $C_2 := C_2(\mu, M) > 0$ such that for any power series*

$$f(z) = \sum_{n=0}^{\infty} a_n z^n, \quad a_n \in [-\mu, \mu], \quad \forall n,$$

there exists a power series with ± 1 coefficients, i.e.,

$$Q(z) = \sum_{n=0}^{\infty} q_n z^n, \quad q_n \in \{-1, +1\}, \quad \forall n,$$

which satisfies

$$|f(z) - Q(z)| < C_1 e^{-C_2/|1-z|} \tag{1}$$

for all $z \in \mathcal{R}_M \setminus \{1\}$.

Figure 1 depicts the boundary of the set $\mathcal{R}_M$ for $M = 1.1$, $M = 2$ and $M = 5$ along with the unit circle, which is the limit as $M \rightarrow \infty$. Note that $\mathcal{R}_1 = [0, 1]$. An alternative description of this set can be given in the polar coordinates by $r \leq \exp(-\cosh^{-1}(1 + (1 - \cos \theta)/(M^2 - 1)))$ where we have assumed that $\cosh^{-1}$ is given its positive value.

In this generalized framework, the fair duel problem only corresponds to approximating the zero function $f \equiv 0$ by power series with ± 1 coefficients. For this case, we can set $\mu = 0$ and $M = 1$.

Note that in general it would be unrealistic to expect close approximations by power series with ± 1 coefficients at arbitrary points inside the unit disc. One extreme example is the point $z = 0$. At this point, $|f(0)| = |a_0| \leq \mu < 1$ whereas $|Q(0)| = 1$. In addition, it is not possible to have a bound of the type $e^{-C/|a-z|}$ near any point $|a| < 1$ as this would imply $f \equiv Q$.

It is clear that the point $z = 1$ can be replaced by $z = -1$ by considering $\tilde{a}_n = (-1)^n a_n$ as input and setting $q_n = (-1)^n \tilde{q}_n$. Also, the theorem extends to the case of arbitrary complex coefficients a_n such that $|\Re(a_n)| \leq \mu$ and $|\Im(a_n)| \leq \mu$ if we allow $q_n = \pm 1 \pm i$.

Apart from constants, the result of Theorem 1 is optimal by the following theorem of Borwein-Erdélyi-Kós.




Figure 1: The boundary of $\mathcal{R}_M = \{z \in \mathbb{C} : |1 - z| \leq M(1 - |z|)\}$ for three different values of M .

Theorem 2 (Borwein-Erdélyi-Kós [4, Thm 5.1]). *There are absolute constants $c_1 > 0$ and $c_2 > 0$ such that for any analytic function F defined on the open unit disc $\mathbb{D}$ that satisfies*

$$|F(z)| \leq \frac{1}{1 - |z|}, \quad z \in \mathbb{D},$$

one has, for any $\alpha \in (0, 1]$,

$$|F(0)|^{c_1/\alpha} \leq e^{c_2/\alpha} \sup_{x \in [1-\alpha, 1]} |F(x)|.$$

To see the optimality, it suffices to set $F(z) = (f(z) - Q(z))/2$. Then for any choice of a_n and q_n in their given range, F satisfies the hypothesis of Theorem 2 and moreover $1 > |F(0)| \geq (1 - \mu)/2$.

2 Proof of Theorem 1

Given any sequence $(a_n)_{n \geq 0}$ that takes values in the interval $[-\mu, \mu]$, we will construct a ± 1 sequence $(q_n)_{n \geq 0}$ via the following algorithm. Let $h = (h_k)_{k \geq 1}$, be a sequence of real numbers (to be specified later) which satisfies

$$\mu + \sum_{k=1}^{\infty} |h_k| \leq 2. \quad (2)$$

We shall call such a sequence μ -admissible. For $n = 0, 1, 2, \dots$, let

$$w_n = \sum_{k=1}^n h_k v_{n-k} + a_n, \quad (3)$$

$$q_n = \text{sign}(w_n), \quad (4)$$

$$v_n = w_n - q_n, \quad (5)$$

with the convention $\text{sign}(0) = 1$. Note also that $w_0 = a_0$.

An easy induction argument gives that $|v_n| \leq 1$ for all n : It is true for $n = 0$ since $v_0 = a_0 - \text{sign}(a_0)$. Assume that $|v_k| \leq 1$ for all $k < n$. Then (2) and (3) yield $|w_n| \leq 2$ and therefore $v_n = w_n - \text{sign}(w_n) \in [-1, 1]$.

Since

$$a_n - q_n = v_n - \sum_{k=1}^n h_k v_{n-k},$$

we have the relation

$$\sum_{n=0}^{\infty} a_n z^n - \sum_{n=0}^{\infty} q_n z^n = \left(1 - \sum_{k=1}^{\infty} h_k z^k\right) \left(\sum_{n=0}^{\infty} v_n z^n\right) \quad (6)$$

for $|z| < 1$. Hence, using the boundedness of v_n , we obtain the estimate

$$|f(z) - Q(z)| \leq \left|1 - \sum_{k=1}^{\infty} h_k z^k\right| (1 - |z|)^{-1}, \quad (7)$$

and the problem is reduced to finding a μ -admissible sequence h such that the power series

$$H(z) = 1 - \sum_{k=1}^{\infty} h_k z^k$$

decays very rapidly to 0 as $z \rightarrow 1$. We shall pick a particular sequence h as follows: Let σ be a positive integer. Let

$$c_\sigma := \frac{\sinh(\pi\sigma^{-1/2})}{\pi\sigma^{-1/2}},$$

and let $h_k := h_k^{(\sigma)}$ be defined via

$$H(z) := H_\sigma(z) := 1 - c_\sigma z - 2c_\sigma \sum_{n=1}^{\infty} \frac{(-1)^n}{\sigma n^2 + 1} z^{\sigma n^2 + 1}. \quad (8)$$

Below we shall estimate the size of $H_\sigma(z)$ for $|z| < 1$. But first we have to show that (2) is satisfied.

We say that σ is μ -admissible if $h^{(\sigma)}$ is μ -admissible. For any $\mu < 1$, this is obviously the case for all large values of σ since $c_\sigma \rightarrow 1$ as $\sigma \rightarrow \infty$. It is easy to find the μ -admissible values of σ explicitly. We have the formula (e.g., [3, p. 268])

$$1 + 2\omega^2 \sum_{n=1}^{\infty} \frac{1}{n^2 + \omega^2} = \pi\omega \coth(\pi\omega), \quad (9)$$

which implies that

$$\begin{aligned} \sum_{k=1}^{\infty} |h_k^{(\sigma)}| &= c_\sigma \left(1 + 2\sigma^{-1} \sum_{n=1}^{\infty} \frac{1}{n^2 + \sigma^{-1}}\right) \\ &= c_\sigma \pi \sigma^{-1/2} \coth(\pi \sigma^{-1/2}) \\ &= \cosh(\pi \sigma^{-1/2}). \end{aligned} \quad (10)$$

Hence σ is μ -admissible if and only if

$$\sigma > \pi^2 / \log^2 \left(2 - \mu + \sqrt{(1 - \mu)(3 - \mu)} \right).$$

We note that the smallest attainable value of σ is 6 and is μ -admissible for $\mu = 2 - \cosh(\pi/\sqrt{6})$. It is easily seen that c_σ is a decreasing function of σ ; therefore $c_\sigma \leq c_6 < 1.3$ for all σ . On that other hand, as $\mu \rightarrow 1$, the lower bound for σ behaves as $\pi^2/2(1 - \mu)$.

Of course the function $H_\sigma(z)$ was not chosen arbitrarily. First, we claim

$$\lim_{z \rightarrow 1} H_\sigma(z) = H_\sigma(1) = 0. \quad (11)$$

The first equality follows from the uniform convergence of $H_\sigma(z)$ on the closed unit disc and the second equality follows straight from the formula (e.g., [3, p. 271])

$$\sum_{n=1}^{\infty} \frac{\cos n\xi}{n^2 + \omega^2} = \frac{\pi}{2\omega} \frac{\cosh(\pi - \xi)\omega}{\sinh \pi\omega} - \frac{1}{2\omega^2} \quad (12)$$

for $\xi = \pi$ and $\omega = \sigma^{-1/2}$.

In order to estimate $H_\sigma(z)$ around $z = 1$, we note that for $|z| < 1$,

$$H'_\sigma(z) = -c_\sigma \left(1 + 2 \sum_{n=1}^{\infty} (-1)^n z^{\sigma n^2} \right) = -c_\sigma \Theta_4(0, z^\sigma), \quad (13)$$

where

$$\Theta_4(\omega, z) := \sum_{n=-\infty}^{\infty} (-1)^n z^{n^2} e^{2in\omega}$$

is the fourth theta-function of Jacobi. Hence, (11) and (13) now provide us with

$$H_\sigma(z) = c_\sigma \int_z^1 \Theta_4(0, s^\sigma) ds. \quad (14)$$

We take the path of integration to be the straight line segment $[z, 1]$ connecting z to 1 to obtain the estimate

$$|H_\sigma(z)| \leq c_\sigma |1 - z| \sup_{s \in [z, 1]} |\Theta_4(0, s^\sigma)|. \quad (15)$$

It is not difficult to estimate $|\Theta_4(0, s^\sigma)|$ near $s = 1$. One way of doing this is the classical method of applying the Poisson summation formula to the modulated Gaussian $f_\lambda(u) := e^{-\pi\lambda u^2} e^{i\pi u}$ where $\lambda > 0$ and $u \in \mathbb{R}$. Since $\widehat{f}_\lambda(\xi) = e^{-\pi(\xi - \frac{1}{2})^2/\lambda}$, we have the identity

$$\Theta_4(0, e^{-\pi\lambda}) = \sum_{n=-\infty}^{\infty} (-1)^n e^{-\pi\lambda n^2} = \frac{1}{\sqrt{\lambda}} \sum_{n=-\infty}^{\infty} e^{-\pi(n - \frac{1}{2})^2/\lambda}, \quad (16)$$

which then extends to any complex λ with $\Re(\lambda) > 0$ by analytic continuation, using the principle branch of $\sqrt{\lambda}$. Clearly the dominating terms for this last expression are given by $n = 0$ and $n = 1$.

We replace λ by $\lambda\sigma/\pi$ in (16) and set $s = e^{-\lambda}$ so that

$$\begin{aligned}
|\Theta_4(0, s^\sigma)| &\lesssim \frac{1}{|\lambda\sigma|^{1/2}} \sum_{n=-\infty}^{\infty} \left| e^{-\frac{\pi^2}{\lambda\sigma}(n-\frac{1}{2})^2} \right| \\
&\lesssim \frac{1}{|\lambda\sigma|^{1/2}} \left[\sum_{n=0}^{\infty} \left| e^{-\frac{\pi^2}{\lambda\sigma}n} \right|^n \right] \left| e^{-\frac{\pi^2}{4\lambda\sigma}} \right| \\
&\lesssim \frac{1}{|\lambda\sigma|^{1/2}} \left[1 + \frac{\sigma}{\Re(\frac{1}{\lambda})} \right] e^{-\frac{\pi^2}{4\sigma}\Re(\frac{1}{\lambda})}, \tag{17}
\end{aligned}$$

where in the last step we have used the inequality $(1 - e^{-x})^{-1} < 1 + x^{-1}$ which is valid for all $x > 0$. (We note that by $A \lesssim B$ we mean $A \leq CB$ for an absolute positive constant C .) Of course, this upper bound works best if we choose λ with $-\pi \leq \Im(\lambda) < \pi$ since $\Re(\frac{1}{\lambda}) = \Re(\lambda)/|\lambda|^2$.

Let us finish the proof of Theorem 1. First we note that we do not lose any generality if we exclude the values of z in the compact set $\mathcal{K}_M := (\mathcal{R}_M \cap \{z : \Re(z) \leq 0\}) \cup \{z : |z| \leq 1/2\}$ since for any choice of a_n and q_n in their given range, the function $f(z) - Q(z)$ is bounded on $\mathcal{K}_M$ by a constant that only depends on M and on this set Theorem 1 does not yield a bound better than a constant anyway. Hence we assume that $z \in \mathcal{R}_M \setminus \mathcal{K}_M$.

Next is a simple lemma that we will employ to finish our analysis.

Lemma 1. *Let $z \in \mathcal{R}_M \setminus \mathcal{K}_M$. There exists an absolute constant $c > 0$ such that if $s = e^{-\lambda} \in [z, 1)$ where λ is chosen such that $-\frac{\pi}{2} \leq \Im(\lambda) \leq \frac{\pi}{2}$, then $\Re(\frac{1}{\lambda}) \geq \frac{c}{M|1-s|}$.*

Proof of Lemma 1. Let us write $s = |s|e^{-i\phi}$ so that $\phi := \Im(\lambda)$ and $\Re(\lambda) = \log \frac{1}{|s|}$. The fact that $z \in \mathcal{R}_M \setminus \mathcal{K}_M$ and $s \in [z, 1)$ imply that $|s| \geq c$ for some absolute constant $c > 0$. Hence we have

$$\log \frac{1}{|s|} \lesssim |s| \log \frac{1}{|s|} \leq 1 - |s| \leq |1 - s|.$$

On the other hand, we also have

$$|\phi| \lesssim |\sin \phi| \lesssim |s| |\sin \phi| = |\Im(s)| = |\Im(1 - s)| \leq |1 - s| \leq M(1 - |s|) \leq M \log \frac{1}{|s|},$$

where the fourth inequality relies on the fact that $\mathcal{R}_M$ is a convex set. This, together with the previous inequality, imply

$$\frac{1}{\Re(\frac{1}{\lambda})} = \log \frac{1}{|s|} + \frac{\phi^2}{\log \frac{1}{|s|}} \lesssim M|1 - s|.$$

This proves the lemma. □

Now, using the lemma, we have the bound

$$\left[1 + \frac{\sigma}{\pi^2 \Re(\frac{1}{\lambda})} \right] e^{-\frac{\pi^2}{4\sigma}\Re(\frac{1}{\lambda})} \lesssim \sigma M e^{-\frac{2C}{\sigma M|1-s|}}. \tag{18}$$

where C is an absolute positive constant. On the other hand, we have

$$|\lambda| \geq \Re(\lambda) = -\log |s| \geq 1 - |s| \geq \frac{1}{M}|1 - s|,$$

so that

$$\frac{1}{|\lambda|^{1/2}} \lesssim \sigma^{1/2} M \left(\frac{C}{\sigma M |1-s|} \right)^{1/2} \lesssim \sigma^{1/2} M e^{\frac{C}{\sigma M |1-s|}}.$$

Hence we obtain the desired estimate

$$|f(z) - Q(z)| \lesssim \sigma^{3/2} M^3 e^{\frac{-C}{\sigma M |1-z|}}$$

which concludes the proof of Theorem 1. $\square$

3 Remarks

3.1 Explicit upper bounds for the optimal decay of bias

For the special case $f \equiv 0$ that corresponds to the fair duel problem, we can set $\mu = 0$, $M = 1$ and choose any $\sigma \geq 6$. Let us call the resulting sequence $q^{(\sigma)}$. Moreover, we are only interested in approximation of $f(z)$ for real values of z . It is easy to check from the proof of Theorem 1 that we now have

$$|B_{q^{(6)}}(\epsilon)| \lesssim \sqrt{\epsilon} e^{-\frac{\pi^2}{24\epsilon}}.$$

Below is the first 50 values of $q_n^{(6)}$ computed using our algorithm. For the compactness of presentation, we list it as a $\{0, 1\}$ sequence rather than a ± 1 sequence.

$$q^{(6)} : 1001010111010101001011101001010111010010111010010111010100101...$$

Note that it would be necessary to employ special numerical methods to compute the terms for arbitrarily large n due to the possibility of the accumulation of rounding errors.

It is interesting that the beginning of the sequence $q^{(8)}$ bears a remarkable resemblance with the Thue-Morse sequence:

$$\begin{aligned} q^{(8)} : & 10010110011101001100101100111010011001011001100101110... \\ \text{TM} : & 100101100111010010110100110010110011100110011001011010... \end{aligned}$$

3.2 Decay of bias for the Thue-Morse sequence

For the completeness of our discussion we present below a short derivation of the decay of bias for the Thue-Morse sequence. Let N_ϵ be the unique integer such that $1 \leq 2^{N_\epsilon} \epsilon < 2$. We have

$$1 \geq \prod_{n=N_\epsilon}^{\infty} (1 - (1 - \epsilon)^{2^n}) \geq \prod_{n=N_\epsilon}^{\infty} (1 - e^{-2^n \epsilon}) \geq \prod_{n=0}^{\infty} (1 - e^{-2^n}) \gtrsim 1;$$

hence it suffices to estimate the product of the first $N_\epsilon = (\log_2 \frac{1}{\epsilon}) (1 + o(1))$ terms. For this it suffices to use the simple inequality $2^n \epsilon \geq 1 - (1 - \epsilon)^{2^n} \geq \epsilon$. We now have

$$2^{-\frac{1}{2}(\log_2 \frac{1}{\epsilon})^2(1+o(1))} = \prod_{n=0}^{N_\epsilon-1} 2^n \epsilon \geq \prod_{n=0}^{\infty} (1 - (1 - \epsilon)^{2^n}) \gtrsim \prod_{n=0}^{N_\epsilon-1} \epsilon = 2^{-(\log_2 \frac{1}{\epsilon})^2(1+o(1))}.$$

3.3 Extensions

The proof of Theorem 1 employed the boundedness of the sequence (v_n) . It is possible to relax this condition by allowing for mild (e.g. sub-exponential) growth of $|v_n|$. This generalization is one possible direction to seek better approximations.

Our algorithm was inspired by sigma-delta quantization; in fact, the particular scheme that we have employed corresponds to an “infinite-order” limit of a family of schemes developed in [5].

Acknowledgements

The author would like to thank Sergei Konyagin for introducing him the fair duel problem and the many valuable discussions. This work was supported in part by the National Science Foundation Grant DMS-0219072.

References

- [1] S. Konyagin, personal communication, 2003.
- [2] J-P. Allouche and J. Shallit, “Automatic Sequences: Theory, Applications, Generalizations,” Cambridge University Press, 2003.
- [3] P. Henrici, “Applied and Computational Complex Analysis,” Wiley, 1991.
- [4] P. Borwein, T. Erdélyi and G. Kós, “Littlewood-type problems on $[0, 1]$,” *Proc. London. Math. Soc.* 79 (1999), 22–46.
- [5] C. S. Güntürk, “One-Bit Sigma-Delta Quantization with Exponential Accuracy,” *Comm. Pure Appl. Math.*, vol. 56, pp. 1608–1630, no. 11, 2003.

C. Sinan Güntürk
Courant Institute of Mathematical Sciences
251 Mercer Street
New York, NY 10012.
`gunturk@cims.nyu.edu`